
SECURITRON
ASSA ABLOY

ASSA ABLOY, the global leader
in door opening solutions



MODEL BACS-12-20	A	B	C
	15	18	6
NOTE: FASTENERS NOT SHOWN ALL DIMENSIONS IN INCHES.			



BACS-24-10 (POWER SUPPLY 24 VAC)

Features

- Hard Wired power supply
- Employs the same multiple zone concept as the BPS Series
- Provides eight (8) automatically breakered outputs with individual control switches and LEDs
- Additional "slave" boards may be ordered to add 8 extra zones
- BACS-12-20 provides 20 amps 12 VAC
- BACS-24-10 provides 10 amps 24 VAC
- **UL Listed**

Operating Temperature

0 to 43C [32 to 110F]

How To Order

Part #	Description
BACS-12-20	Power Supply 12 VAC 20 Amp
BACS-24-10	Power Supply 24 VAC 10 Amp
BACSH-12-20	Power Supply 12 VAC 20A 220 VAC
BACSH-24-20	Power Supply 24 VAC 10A 220 VAC

© 2015, Hanchett Entry Systems, Inc., an ASSA ABLOY Group company.

BACS-24-10 POWER SUPPLY 24 VAC (cont'd)

Architectural Specification

A. The power supply shall be produced by an ISO 9001 certified manufacturer

B. The power supply shall have a limited lifetime warranty covering malfunction and abuse.

C. The power supply shall furnish 24 VAC or 12 VAC (voltage specific) and shall be U.L. class 2 listed.

D. The power supply shall employ a multiple zone concept providing 8 separate outputs.

E. The circuit breakers shall be provided to divide the load, LED'S shall monitor zone status (voltage, no voltage) and slide switches shall be provided to connect or disconnect the load from power.

F. The power supply shall be supplied complete requiring only 120VAC to the fused input and shall be supplied in an enclosure.

G. The power supply shall be provided with emergency release terminals that allow the release of all devices upon activation of the fire alarm system.