INSTRUCTIONS
FOR
8007S SENSITIVE RELAY BASE

1. SUPPLY CONSTANT COIL VOLTAGE TO TERMINALS MARKED (+) AND (-) OBSERVING POLARITY.

2. FOR A *POSITIVE* TRIGGER, CONNECT (-) TO (-) TRIG AND (-) TO CONSTANT NEGATIVE OF TRIGGER SOURCE. CONNECT (+) TRIGGER TO POSITIVE TRIGGER OUTPUT.

3. FOR A *NEGATIVE* TRIGGER, CONNECT (+) TO (+) TRIG AND (-) TO CONSTANT NEGATIVE OF TRIGGER SOURCE. CONNECT (-) TRIGGER TO NEGATIVE TRIGGER OUTPUT.

***NOTE*: A POSITIVE TRIGGER GOES FROM GROUND TO A POSITIVE VOLTAGE. A NEGATIVE TRIGGER GOES FROM A POSITIVE VOLTAGE TO GROUND.**

ALARM CONTROLS CORPORATION
19 BRANDYWINE DRIVE
DEER PARK, NY 11729
800 645-5538