LED Canopy Light Installation Instructions

CAT#: 71411A

CAUTION:

1. Do not use the electric generator to test this LED fixture.
2. This fixture is to be installed by a licensed electrician only, abiding by all local and national electrical codes.
3. Please turn off the power before installation or maintenance.
4. Proper grounding to this fixture is required to ensure safety.

ATTENTION:

1. Please check for any damage during shipping. If so, please contact Morris Products immediately.
2. Please read the installation instruction carefully to check and confirm that all parts and accessories are included.

Wiring Diagram:



Installation Method #1 :

1. Attach one side of the safety rope to the back of the fixture (Figure 1).
2. Use a drill to create fixed holes through the ceiling (Figure 2).
3. Attach the other side of the safety rope to the ceiling, then connect the wiring of the fixture to main supply, according to both local and national electrical codes. Make sure there is good protection on the wire joint. Then, attach and secure the fixture on the ceiling using the included screws. (Figure 3).


Figure 1



Figure 2


Figure 3

Installation Method #2:

1. Connect the wiring to the local power supply using the 3/4"NPT Stem (Figure 4).
2. Screw the fixture to the 3/4"NPT Stem (Figure 5).


Figure 4


Figure 5

Installation Method #3:

1. Attach and secure the mounting bracket to the back of the fixture using the included screws (Figure 6).
2. Unscrew the nut from 3/4"NPT stem, bring the stem hole on mounting bracket through 3/4"NPT stem, then screw the nut back to 3/4"NPT, and secure it in place (Figure 7).
3. Make proper wiring connections as per the wiring diagram on page 1.


Figure 6


Figure 7

1. Drill holes on the top ceiling, line them up to the holes on the mounting bracket (Figure 8).
2. Insert the supplied rubber pieces into the alignment holes on the ceiling, then secure the mounting plate on the ceiling using the included screws (Figure 9).
3. Attach the fixture to the mounting plate using the included screws (Figure 10).
4. Make proper wiring connections as per the wiring diagram on page 1.



Figure8


Figure9


Figure10

WARNING:

MIN 75°C SUPPLY CONDUCTORS
THIS PRODUCT MUST BE INSTALLED BY A QUALIFIED ELECTRICIAN ONLY, ABIDING BY ALL LOCAL AND NATIONAL ELECTRICAL CODES.