



PRODUCT FEATURES

- Backup device in case of exit sensor failure per BOCA, NFPA, IBC, and VBC code
- SPST 3 Amp wet N/C contacts
- Momentarily pressing the EEB releases the door for 30-seconds
- Re-triggerable for added 30-second release
- Field-selectable 12VDC or 24VDC to match lock voltage
- Interchangeable green and red lenses included standard
- MagnaCare Lifetime Replacement No Fault Warranty

PRODUCT OPTIONS

- Single gang
- Narrow stile
- EEB2 includes standard lenses plus blue ADA lens
- Illumination kits

SPECIFICATIONS

- (EEB2, EEB3N only)
- ANSI/UL 294 Listed
 - CSA-C22.2 No.205 Listed
 - CSFM – California State Fire Marshal

EEB

Exit Buttons

Redundant Backup Ensures Safe Egress

Install the EEB Emergency Exit Button next to the door to provide additional safety and redundancy as required by code when using a motion detector for a request-to-exit device.

» MODELS

PART #	Description
EEB2	EEB w/ 30 Sec. Timer - SG, Grn/Red/Handicap
EEB3N	EEB w/ 30 Sec. Timer - Narrow Stile, Grn/Red
PB2-LK	Illumination Kit for PB2E, PB5E, EEB2 Series Push Buttons
PB3-LK	Illumination Kit, Grn/Red for PB3E/EEB3N Series



Note: Securiton's UL294 certification indicates that when the EEB is used with the XMS Motion Sensor, it meets the NFPA Life Safety Code 101 requirements for exit of access-controlled egress doors.



DUAL VOLTAGE



SECURITRON
ASSA ABLOY